



The BigShot ABY is an ultra compact, 100% passive foot switch that provides ABY amp switching capabilities with A or B toggle and A + B combine functionality. It features 'straight wire' true-bypass connectivity for the purist. This assures the guitar signal is routed directly to the amp without any buffering, loading or tone altering circuits.

To add versatility, the BigShot ABY has a built-in transformer that can be engaged to eliminate troublesome ground loops. Once engaged, you can use the 180° polarity reverse switch to ensure your amps are in-phase. An additional tuner output is offered allowing you to split the input signal and send it to another device.

When powered by an external 9V power supply or pedalboard power brick, full sized LED's provide instant on-stage amplifier status. The compact yet ultra rugged design makes the BigShot ABY ideal for pedalboards where space is always at a premium.

BigShot ABY - Order # R800 7210

**Features**

- True bypass ABY amp selector with tuner out
- On-board transformer to eliminate ground buzz
- 180° polarity reverse to phase-align amps
- Bright LED status indicators

**Applications**

- Switch or combine two amps
- Switch between two instruments and one amp
- Tuner output is always on for quick adjustments

**Cool Stuff**

- Plug and play easy to use
- 100% passive audio circuit
- Compact and rugged, perfect for pedalboards
- Works with all instruments: guitar, bass, keys

**Dimensions (W x D x H)**

- 3.6" x 4" x 2" (92mm x 100mm x 51mm)
- 3 Year transferable warranty

- 9VDC** - Power supply connection (for LED's only).
- A-B OUTPUTS** - Allows for A/B/A+B combinations.
- TUNER** - Keeps the tuner out of the main audio path.
- INPUT** - Input for your guitar, bass and keyboard.


- OUTPUT-B 180°** - Polarity reverse to phase align two amps.
- OUTPUT-B LIFT** - LIFT disconnects signal ground to further reduce noise.
- OUTPUT-B ISO** - Transformer breaks ground loops that cause hum and buzz.



- BOTH** - Stomp to activate both outputs with LED indicators.
- A-B** - Stomp to select the active output with LED indicators.


**Switch Between Clean and Dirty Amps**

Easy to use amp switcher made for tone purists. Makes a straight-through connection to your amp for best tone. Transformer isolation from ground loop hum and phase reverse to align speaker phase.



**Silent Tuning Setup**

By connecting your tuner to OUTPUT-B you can toggle between an amp and tuner for "silent tuning". Alternatively, by connecting the tuner to the always-on TUNER output you can tune on the fly.



**Using the ABY to switch channels to an amp**

The BigShot ABY can also be used to switch channels on older vintage amps that do not have remote switching. Simply send the OUT-A and OUT-B to the two channels on your amp and select channels as needed.

